



WDR COLOR CCD CAMERA with
DAY & NIGHT

INSTRUCTION MANUAL

SHC-721AN/AP/APH

About this manual

Before installing and using the camera, please read this manual carefully. Be sure to keep it handy for later reference.



SALES NETWORK

· SAMSUNG TECHWIN CO., LTD.

145-3, Sangdaewon 1-dong, Jungwon-gu, Seongnam-si,
Gyeonggi-do 462-703, Korea
TEL : +82-31-740-8137~8141 FAX : +82-31-740-8145

· SAMSUNG OPTO-ELECTRONICS AMERICA, INC.

ELECTRONIC IMAGING DIV.
40 Seaview Drive, Secaucus, NJ 07094, U.S.A
TEL : +1-201-902-0347 FAX : +1-201-902-0429

· SAMSUNG TECHWIN MOSCOW OFFICE

Korp 14, 37-A, PR-KT, Leningradsky, Moscow 125167, Russia
TEL : +7-95-258-9296,9298 FAX : +7-95-258-9297

· SAMSUNG OPTO-ELECTRONICS UK, LTD.


Samsung House, 1000 Hillswood Drive, Hillswood Business
Park Chertsey, Surrey KT16 0PS
TEL : +44-1932-45-5308 FAX : +44-1932-45-5325

· TIANJIN SAMSUNG OPTO-ELECTRONICS CO., LTD.


7 Pingchang Rd, Nankai Dist, Tianjin 300190, P.R China
TEL : +86-22-2761-4724(33821) FAX : +86-22-2761-6514

www.samsungtechwin.com
www.samsungcctv.com

P/No. : Z6806-0484-01B
VAN 05. 04



SAMSUNG CCD CAMERA



The lightning flash with an arrowhead symbol, within an equilateral triangle is intended to alert the user to the presence of uninsulated "dangerous voltage" within the product's enclosure that may be of sufficient magnitude to constitute a risk of electric shock to persons.



The exclamation point within an equilateral triangle is intended to alert the user to the presence of important operating and maintenance (servicing) instructions in the literature accompanying the appliance.

INFORMATION - This equipment has been tested and found to comply with limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

WARNING - Changes or modifications not expressly approved by the manufacturer could void the user's authority to operate the equipment.

CAUTION : To prevent electric shock and risk of fire hazards:

- ◆ Do NOT use power sources other than that specified.
- ◆ Do NOT expose this appliance to rain or moisture.

This installation should be made by a qualified service person and should conform to all local codes.

Wide Dynamic Range(WDR)

SV-II DSP chip built-in SAMSUNG TECHWIN allows the camera to find the best picture conditions in any environment and automatically gives a necessary light level compensation, so you can always obtain the clear picture, the finest detail and perfect light contrast.

Fine Picture Condition Under Very Low Illumination (Sense up)

1/3 high density CCD and digital processor permit high quality pictures to be captured in very low light condition.

High Resolution

The horizontal resolution of 500TV lines at Color mode and 550TV lines at BW mode can be achieved by using a high density CCD having Double Speed 410,000 pixels SONY CCD, which provides clear, noiseless and reliable pictures.

Day & Night

The camera provides automatic mode changeover by sensing day or night conditions. It can change color mode in the day condition for optimal color and BW mode in night condition for clear identification.

Motion Detection

The camera transmits an alert signal to the REMOTE jack when it detects motion of an object. If you connect an optional alarm to the camera, you can get the effective surveillance.

VIDEO/DC Lens Selectable

The camera accepts 2 types of auto iris lenses (DC type/VIDEO type) and is set with the VIDEO/DC selection switch.

Electronic Iris

The electronic iris shutter is automatically controlled at the speed of 1/60-1/200,000sec (NTSC Models), 1/50-1/200,000sec (PAL Models)

Controlled by OSD menu and RS-232C

You can control the camera using OSD menu and RS-232C jack at a remote place.

SSNR(Samsung Super Noise Reduction) CHIP

SHC-721AN/AP/APH has an assistant DSP chip that can remove image noise efficiently and it shows clean and obvious image in low luminance.

The camera needs periodic inspection.

Contact an authorized technician for inspection.

Stop using your camera when you find a malfunction.

If you use your camera around smoke or unusual heat for a long time, a fire may be caused.

Do not install the camera on a surface that can not support it.

Unless the surface is suitable, it could cause falling or other hazards.

Do not hold plug with wet hands.

It could cause an electric shock.

Do not disassemble the camera.

It may result in fire, electric shock or other hazards.

Do not use the camera close to a gas or oil leak.

It may result in fire or other hazards.

Correct Disposal of This Product (Waste Electrical & Electronic Equipment)



(Applicable in the European Union and other European countries with separate collection systems) This marking shown on the product or its literature, indicates that it should not be disposed with other household wastes at the end of its working life. To prevent possible harm to the environment or human health from uncontrolled waste disposal, please separate this from other types of wastes and recycle it responsibly to promote the sustainable reuse of material resources. Household users should contact either the retailer where they purchased this product, or their local government office, for details of where and how they can take this item for environmentally safe recycling. Business users should contact their supplier and check the terms and conditions of the purchase contract. This product should not be mixed with other commercial wastes for disposal.

Contents

Precautions	8	Operating Your Camera	21
Composition	10	■ Configuration of The Menu	21
Name and Function of Each Part	11	■ Setting Up The Menu	22
■ Front	11	• CAMERA ID	23
■ Side	12	• BACKLIGHT	26
■ Bottom	13	• WHITE BALANCE	27
■ Back	14	• MOTION DETECTION	28
Connection	15	• LENS	32
■ Lens	15	• SHUTTER SPEED CONTROL	33
• Installing Auto Iris Lens		• SESE UP	35
• Installing C/CS-Mount Lens		• GAIN	36
■ Connecting to Monitor	19	• SSNR	36
■ Connecting to Power	20	• SPECIAL	37
		Using Reomte Jack / MD Output	40
		Troubleshooting	41
		Specifications	43



Precautions

Do not install the camera in extreme temperature conditions.



Only use the camera under conditions where temperatures are between -10°C and $+50^{\circ}\text{C}$. Be especially careful to provide ventilation when operating under high temperatures.

Do not install or use the camera in an environment where the humidity is high.




It can cause the image quality to be poor.

Do not drop the camera or subject them to physical shocks.




It can cause malfunctions to occur.

Never keep the camera face to strong light directly.



It can damage the CCD.

Do not install the camera under unstable lighting conditions.



Severe lighting change or flicker can cause the camera to work improperly.

Do not touch the front lens of the camera.



It is one of the most important parts of the camera. Be careful not to be stained by fingerprint.

Do not expose the camera to rain or spill beverage on it.



If it gets wet, wipe it dry immediately. Liquids can contain minerals that corrode the electronic components.




Notes


- If the camera is exposed to spotlight or object reflecting strong light, smear or blooming may occur.
- Please check that the power satisfies the normal specification before connecting the camera.

Composition


1. WDR Color CCD Camera
SHC-721A



2. Auto Iris Lens Plug



3. Remote Plug



4. L-Wrench



5. C-Mount Adapter




6. Instruction Manual




Name and Function of Each Section

Front



Name and Function of Each Section

Side



Menu Setup Buttons

- **SET Button:** Used to access menu mode. Also used to confirm the setting.
- **UP/DOWN Button:** Used to choose the desired menu item. It also moves the cursor up or down in the menu screen.
- **LEFT/RIGHT Button:** Used to change the parameter of the selected menu item. It also moves the cursor the left or right in the menu screen.


Bottom

Tripod Mounting Hole



Used to install the camera on an optional tripod. The tripod must be equipped with the screw specified as shown below.

1/4"-20 UNC (20 THREAD)

L: 4.5mm±0.2mm (ISO standard),
or 0.197" (ASA standard)




Tripod Mounting Bracket



You can remove and install this bracket on the top of the camera. You must use the supplied screw or the equivalent (within 4mm). If not, the bracket may not be fixed properly.

Back



■ LENS

The lens is not supplied with this camera. Purchase a lens suitable for your environment. This camera accepts the auto iris lens and both C-and CS-mount lens.




Notes


- If the lens is marked with fingerprints or other marks, the image quality might be poor.
- It is recommended to use a high quality lens to improve the image quality under low illumination.
- For using main functions it is recommended to use Auto Iris Lens with DC type.

Installing Auto Iris Lens

1. Peel approximately 8mm from the end of the lens cable outer cover.



2. Peel approximately 2mm from the end of the cable inner cover.



Connection



3. Remove the cover from the iris lens plug supplied, and solder the lens cable to the plug as shown below.

• Video type :

- No. 1 Pin --- Red (Power source)
- No. 2 Pin --- N.C
- No. 3 Pin --- White (Video signal)
- No. 4 Pin --- Black (GND)


• DC type :

- No. 1 Pin --- Damping -
- No. 2 Pin --- Damping +
- No. 3 Pin --- Drive +
- No. 4 Pin --- Drive -




4. Remove the protective cap, and attach the lens to the camera by turning clockwise.

5. Connect the lens plug to the auto iris connector on the right side of the camera.



6. Set the DC/VIDEO selection switch to DC or VIDEO according to the type of the lens.




Installing C/CS-Mount lens

Before mounting a lens, please check whether it is a C-mount or CS-mount lens. The back focus is set for the CS-mount lens at the factory.


• Mounting a CS-Mount lens

After removing the protecting cap, attach the lens into the camera by turning clockwise.



Notes

- Use the lens under the specification as shown. Otherwise the lens can damage the camera or abnormal fixing may result.




- A heavy lens may disturb the balance with the camera and possibly result in damage. Don't use a lens heavier than 450g.
- It is recommended to set the lens ALC mode to Av mode (Average). Pk mode can be occurred hunting.


Connection

• Mounting a C-Mount lens

1. Attach the C-Mount lens adapter by turning clockwise.




2. Attach the lens to the camera by turning clockwise.




■ Connecting to Monitor

Connect the VIDEO Out jack to the monitor VIDEO In jack.



- As the connecting method varies with the instruments, refer to the manual supplied with the instrument.
- If necessary, you can connect the monitor to the REMOTE jack on the back of your camera. For details, see page 40.
- Only connect the cable when the power is turned off.
- Set the 75W/Hi-Z selection switch as shown below if you have an intermediate device.




■ Connecting to Power

Each model has different power specification. Please check the name of the model and power specification before connecting to power source.

For AC / DC Power Type

- The wire is polarized. Be sure to connect the wire that white line is on covering to '-' terminal and connect the other one to '+' terminal.
- Use AC 24V/300mA or DC 12V/500mA power source for SHC-721AN/AP



Resistance of copper wire [at 20C° (68F)]

Copper wire size (AWG)	#24(0.22mm ²)	#22(0.33mm ²)	#20(0.52mm ²)	#18(0.83mm ²)
Resistance (Ω / m)	0.078	0.050	0.030	0.018
Voltage Drop (V/m)	0.028	0.018	0.011	0.006

- As the voltage drop according to the length of the cable in the above table, a camera may malfunction if there is an excessively long cable run.

* Voltage for camera operation: 12V DC ±10%

* Voltage drops in the above table are variable according to types of cable manufacturer.

For High Voltage Type

- The wire is non-polarized.
- Use AC 230V~, 50Hz power source for SHC-721APH



Notes

- Be sure to connect power only after all the installation is complete.
- Note that AC or DC adaptor is not supplied with camera.
- Use the UL listed, class 2 power transformer of AC 24V adaptor.
- Ground should be connected to the GND terminal.


■ Configuration of The Menu

SETUP MENU	— CAMERA ID (see page 23)
	• OFF • ON
	— BACKLIGHT (see page 26)
	• WDR • BLC • OFF
	— WHITE BAL. (see page 27)
	• W-ATW • S-ATW • AWC • MANUAL
	— MOTION DET. (see page 28)
	• OFF • MD1 • MD2
	— LENS (see page 32)
	• DC / Video • Manual
	— SHUTTER (see page 33)
	• OFF • 1/100 (1/120) • ESC • MANUAL
	— SENSE UP (see page 35)
	• Auto • OFF
	— GAIN (see page 36)
	• OFF • AGC-L • AGC-H
	— SSNR (see page 36)
	• OFF • LOW • MIDDLE • HIGH
	— SPECIAL (see page 37)
	• COLOR • SYNC • PRIVACY • PRESET
	• END • EXIT
	EXIT


Operating Your Camera

■ Setting Up The Menu


Use the five Setup Menu buttons on side of the camera.



1. Press the SET button to access the setup mode.
 - Setup menu is displayed on the monitor screen.



2. Select the desired feature using the UP or DOWN button.
 - Each time you press the UP or DOWN button, the arrow indicator moves up or down.
 - Move the arrow indicator to the desired feature item.



3. Change the status of the selected feature using the LEFT or RIGHT button.
4. When completed, move the arrow indicator to 'EXIT' and press the SET button.



Notes

- For the mode with ↓ you can access submenu.
- You can access submenu using SET button.

Camera ID


If you enter a camera ID, the name will be displayed in the screen monitor.

1. Press the SET button to display the setup menu and move the arrow indicator to 'Camera ID' using the UP or DOWN button.
2. Set 'Camera ID' to 'ON' using the LEFT or RIGHT button.




Notes

- If the camera ID feature is set to 'OFF', the name will not be displayed in the monitor.




Operating Your Camera

3. Press SET button.



4. You can enter up to 16 characters.

- 1 Move the cursor to character-enter location by using the LEFT or RIGHT button.
- 2 Select the desired character by using UP or DOWN button.
 - The factory default characters are A, B, ..., a, b, ..., ., -, ..., 0, 1..., 8, 9



- 3 Press the SET button to confirm the blinking character. The first character is saved and the cursor in the bottom of the screen moves to the next position.
- 4 Repeats steps 1, 2 and 3 until you create the full name you want.




Notes

- If you make a mistake while entering name
Move the cursor to 'Clr', press 'SET' button.
After erasing the character from right to left, correct the character again.

5. Select the position at which the camera ID will be located on the screen.

- 1 Move the cursor to 'Pos' and press SET button.



- 2 The camera ID is displayed on the bottom-left of the monitor screen.
(Default position)



- 3 Select the position by using the 4-directional buttons, then press the SET button to confirm the position.




6. When completed, move the cursor to 'End' and press SET button.

Operating Your Camera

Backlight


SV-II DSP chip built-in provides intelligent light level control to overcome the severe Backlight conditions.

1. Press the SET button to display the setup menu and move the arrow indicator to 'Backlight' using the UP or DOWN button.



2. SET 'Backlight' to the desired mode using the LEFT or RIGHT button.

- WDR: In case that bright and dark parts exist on the screen at the same time, your camera allows you to see both parts clearly
- BLC: When the image is in front of strong background lighting, your camera allows you to get the clear image
- OFF: Deactivation



3. Press the 'SET' button.

- When 'WDR' is chosen, you can adjust the level.



You can select the level from -4 to 4. WDR sensitivity is increased or decreased.

4. When completed, press the SET button.




Notes

- If you select ESC or manual in 'shutter' menu, you can't use WDR mode.
- If you select WDR mode, the following phenomenon may appear by lighting condition. In these cases do not select WDR mode.
 - ① Unnatural color change or unnatural phenomenon on the screen
 - ② Noise of bright part on the screen
- According to the area of bright part on the screen there may be the difference of WDR performance so be sure to adjust the degrees of the visual angle when installing your camera.
- If you increase WDR level, unnatural phenomenon may appear.
- For the optimal WDR performance, in case of observing the object that is in the place of the changing illumination, use Auto Iris Lens with DC type.

White Balance Control

Your camera provides 4 'White Bal.' control modes. You can select the most suitable one. You can adjust the white balance.

1. Press the SET button to display the setup menu and move the arrow indicator to 'White Balance' using the UP or DOWN button.
2. Set 'White Bal.' to the desired mode using LEFT or RIGHT button.



The four white balance control modes are as follows :

- W-ATW(Wide Auto Tracking White balance): When color temperature is 2400-12000K, select this mode. (EX. a fluorescent lamp, outdoor)

Operating Your Camera

Ⓞ **S-ATW(Special Auto Tracking White balance):** When color temperature is 1800-6000K, specially in sodium lamp, select this mode. (EX. sodium lamp, inside the tunnel)

Ⓞ **AWC(Auto White balance Control):** The white balance is automatically adjusted in a specific environment. In order to obtain the best result, press the SET button while the camera focuses on white paper. If the environment including the light source is changed, you have to adjust the white balance again.

Ⓞ **Manual:** To fine adjust, select the Manual mode. You can increase or decrease the red or blue factor while monitoring the difference on the screen. Set to 'Manual' mode and press the SET button. Increase or decrease the value for red(R-Gain) and blue(B-Gain), watching the color of the picture, and press the SET button when you obtain the best color.



Notes


- Proper White Balance may not be obtained under the following conditions, in these cases select the AWC mode.
 - ① When the scene contains mostly high color temperature object, such as a blue sky or sunset.
 - ② When the scene is dim.
 - ③ If your camera faces fluorescent lamp directly or is installed in the place of the changing illumination.

Motion Detection

Your camera transmits an alert signal when it detects motion of an object on the screen. If you connect the camera to an external alarm, you can pay attention to the screen when the alarm sounds. This feature is useful when you have to monitor several screens simultaneously. Whenever your camera detects motion of object displaying 'Motion Detected' with the number counted up on the screen.

1. Press the SET button to display the setup menu and move the arrow indicator to 'Motion Det.' using the UP or DOWN button.

2. Set 'Motion Det.' to the desired mode using LEFT or RIGHT button.



Ⓞ **MD1:** Your camera detects the object's motion by outline or difference of a color tone, so this mode is very useful for the daytime or observing small moving object.


① Press SET button.



② Move the arrow indicator to 'Area Set' using UP and DOWN button, and then press the SET button.


③ Set the areas you want to observe.

• You can adjust the top, bottom, left and right base lines by 13 steps from top to bottom, 18 steps from left to right with an increment of 1.



Operating Your Camera

- Move the arrow indicator to 'Top' using the UP or DOWN button and increase or decrease the value using the LEFT or RIGHT button. Repeat the procedure for bottom, left and right.



- When completed, press SET button.




Notes

- If you set some areas of 48 areas, your camera detects the object's motion within the areas you set.

- MD2:** Your camera detects object's motion by the variation of brightness, so this mode is very useful for night or observing large moving object. Also MD2 enables you to set separated areas.

- Press SET button.
- Move the arrow indicator to 'Area Set' like MD1.
- Set the areas you want to observe.



- Move the cursor to the area you want to observe, and then press the SET button.

- After setting, move the cursor to edge in any direction and then press the button just one more, let 'End' blink.
- Press the SET button.



Notes

Tips on Using the Motion Detection Feature

- As you increase or decrease MD Level, the areas' sensitivity is increased or decreased for object.
- After selecting zone and sensitivity, perform a test operation to make sure it works properly.
- If the lighting flickers, the motion detection feature might not work properly.
- The object should occupy 10% or more of its zone. The bigger the object, the higher sensitivity.
- If the brightness of an object changes rapidly by sudden lighting change, the camera may detect it as a motion.
- Your camera can count up to 999. If you reset your camera with selecting 'Reset' in Special menu or turn it off and on, your camera'll count up from 0.
- When this feature is activated, another algorithm may take more time to be operated.
- This system does not guarantee prevention of fires or thefts. The manufacturer is not responsible for any accident or damage.
- You can use the MD output terminal jack on the rear of the camera to connect an external alarm device. For details, see page 40.




Operating Your Camera

Lens Selection

You can set the type of the lens, and control the brightness of the screen.

1. Press the SET button to display the setup menu and move the arrow indicator to 'Lens' using the UP or DOWN button.
2. Set 'Lens' to the desired mode using LEFT or RIGHT button.
 - You can select from DC / Video, Manual



- DC / Video: When using auto iris lens

When using Auto Iris Lens with Video type

- ① Adjust ALC volume on the lens properly. Normally ALC volume should be turned all the way to Av(Average).
- ② According to the type of the lens used, the lens may not perform properly. In such a case, adjust the volume level on the lens.
- ③ For adjusting the volume level set 'Auto Lens VR Adjust' level in submenu of the 'Video' mode to the middle of bar between ▷◁. (adjust the level in the place with more than 300lux)



- Manual: When using manual lens

- If you select 'DC' mode, you can adjust the desired Brightness.



Notes


- When the auto iris lens is mounted, you have to set the DC/Video selection switch on the side of the camera properly according to the type of the lens. The setup window displays DC or Video according to status of this selection switch. (refer to page 12 picture)

3. When completed move the arrow indicator to 'END' and press the SET button.

Shutter Speed Control

You can control brightness of the screen by the shutter speed.


1. Press the SET button to display the setup menu and move the arrow indicator to 'Shutter' using the UP or DOWN button.
2. Set 'Shutter' to the desired mode using the LEFT or RIGHT button.
 - OFF: Deactivation
 - 1/100(1/120: PAL Models): Flickerless mode (When WDR mode is off)
 - ESC: When setting the optimal shutter speed automatically
 - Manual: When setting shutter speed manually




3. If you choose 'Manual', select the optimal shutter speed.

Operating Your Camera

- You can select speed from '1/60' to '1/200,000'sec (NTSC Models), '1/50' to '1/200,000'sec (PAL Models).
- When the shutter speed is increased or decreased using the LEFT or RIGHT button, you can find the difference by monitoring the brightness of the screen.



NTSC Models



PAL Models

4. When completed, press the SET button.




Notes

- For effective 1/100 mode set WDR mode in Backlight menu to OFF. 1/100 mode is not effective with WDR mode.
- If the camera directly faces strong fluorescent light with 'ESC' mode, the image may become unstable.
- If you choose 'ESC', you can adjust the brightness of monitor screen using the LEFT or RIGHT button.
- If you choose ESC or Manual mode, you can't use WDR mode in 'Backlight' menu.
- If you select manual mode, Sense up is not operated.

Sense up

You can always get the clear image with this function under night or low-lighting level.

1. Press the SET button to display the setup menu and move the arrow indicator to 'Sense up' using the UP or DOWN button.
2. Set 'Sense up' to the desired mode using the LEFT or RIGHT button.
 - ☉ **Auto**: When your camera is under night or low-lighting level, select this mode.
 - ☉ **OFF**: Deactivation



Notes

- If you press the set button on 'Auto' mode. You can adjust brightness by increasing or decreasing the shutter speed. (EX. x2, ..., x32, x64, ..., x128)
- If you increase the number of shutter speed, moving object gets a more afterimage.
- Under Sense up activated noise, sports or a whitish phenomenon may appear in the picture as the sensitivity of the camera is increased. This is normal phenomenon.

Operating Your Camera


Gain

To get brighter picture.

1. Press the SET button to display the setup menu and move the arrow indicator to 'GAIN' using the UP or DOWN button.

2. Set 'gain' to desired mode using the LEFT or RIGHT mode.

- AGC-H: Gain is increased or decreased from 0 to 30dB automatically as following the illumination.
- AGC-L: Gain is increased or decreased from 0 to 27dB automatically as following the illumination.
- OFF: Deactivation



SSNR (Samsung Super Noise Reduction)

To reduce the noise on the screen.


1. Press the SET button to display the setup menu and move the arrow indicator to 'SSNR' using the UP or DOWN button.

2. Set 'SSNR' to desired mode using the LEFT or RIGHT mode.

- LOW: low reduction of the noise
- MIDDLE: middle reduction of the noise

○HIGH: high reduction of the noise

○OFF: Deactivation



Notes

- If you change the 'GAIN' menu from AGC-L to AGC-H, sensitivity is increased as well as noise on the screen.

SPECIAL



1. Press the SET button to display the setup menu and move the arrow indicator to 'SPECIAL' using the UP or DOWN button.

Operating Your Camera

2. Press the SET button.

- **COLOR** : choose color or B/W mode
 - ON : color mode - OFF : B/W mode
 - AUTO1 : generally color mode, B/W mode in low luminance.
 - AUTO2 : AUTO2 is identical with AUTO1 under SENSE UP : AUTO condition.

Notes

- When you use Auto Iris Lens with Video type, do not set the level on the lens to too low, Color/BW may not change over automatically.
- When Gain in SET UP menu is OFF, Color / BW do not change over automatically.
- If Gain is OFF, you can select ON or OFF on COLOR menu.
- For the stable operation, whenever the mode is changed over between color and BW mode, five setup menu buttons on the camera do not operate for about 3 seconds.
- The burst signal doesn't come out with BW mode, so when connecting with peripheral equipments be sure to check the specification of those.
- The object may be more out of focus when using a source of near-infrared light than using the visible light.


- **SYNC** : Two SYNCHRONIZATION modes are available INTERNAL and EXTERNAL LINE-LOCK. In LINE-LOCK mode, it synchronizes the video signal between cameras without a synchronous generator. The line-lock synchronization is only used in the areas of 60Hz (NTSC Models) / 50Hz (PAL Models).
 - INT : Internal synchronization
 - OFF : External line-lock synchronization
- If you choose 'L/L', you can adjust the desired phase. Press the SET button.
- You can adjust the desired phase from 0 to 270.

LINE LOCK
PHASE : 225
PRESS SET TO RETURN

Notes

- When the power frequency is 50Hz, you can not use line-lock mode(NTSC Models).
- When the power frequency is 60Hz, you can not use the line-lock mode(PAL Models).
- 'Sync.' mode is fixed to 'INT' in DC 12V input power.


- **PRIVACY**: To mask area which you want to mask
 - OFF: Deactivation
 - ON: Privacy mode activated
- Press the SET button.



- Move the arrow indicator to area you want to mask.
 - Set 'ON' using LEFT or RIGHT button.
 - Press the SET button and then set the area's bounds with the method like MD1 Set. (see page 29)
 - When completed, press the SET button.
- **PRESET**: To reset your camera to factory default condition
 - **END**: To move Top-menu
 - **EXIT**: To finish setting menu

Using Remote Jack / MD Output

If you connect a remote plug to the REMOTE jack on the rear of the camera as shown below, you can access the menu setup mode from a remote place.



1. RS-232C Communication Setting.

- Mode : Serial
- Data Bit : 8
- Bit/sec : 19200bps
- Stop Bit : 1
- Port : Com1
- Parity : None

2. Setup menu Command.

Setup menu	Command	Byte
Set	AA, EE, 0F, CC, 55	5
Up	AA, EE, 1E, CC, 55	5
Down	AA, EE, 1D, CC, 55	5
Left	AA, EE, 1B, CC, 55	5
Right	AA, EE, 17, CC, 55	5

3. MD(Motion Detection) output Signal Level



Notes

- You must turn the camera power off when you connect or remove the remote plug.

Troubleshooting

If you have trouble operating your camera, refer to the following table. If the guidelines do not enable you to solve the problem, contact an authorized technician.

Problem	Solution
Nothing appears on the screen.	<ul style="list-style-type: none"> • Check that the power cord and line connection between the camera and monitor are fixed properly. • Check that you have properly connected VIDEO cable to the camera VIDEO output jack. • Check that the DC/VIDEO selection switch on the side of the camera is set to a proper position according to the type of your auto iris lens. • Are you using Auto Iris Lens with VIDEO type? Adjust VR Level properly (refer to page 32)
The image on the screen is dim.	<ul style="list-style-type: none"> • Is lens stained with dirt? Clean your lens with soft, clean cloth. • Set the monitor to proper condition. • If the camera is exposed to too strong light, change the camera position. • Adjust the lens' focus properly.
The image on the screen is dark.	<ul style="list-style-type: none"> • Adjust the contrast feature of the monitor. • If you have an intermediate device, set the 75Ω / Hi-Z properly. (refer to page 19) • Are you using the Auto Iris Lens? Adjust the level on the lens properly.
The camera is not working properly, and the surface of the camera is hot.	<ul style="list-style-type: none"> • Check that you have properly connected the camera to an appropriate power source. (refer to page 20)

Troubleshooting



Problem	Solution
Motion Detection function is not active.	<ul style="list-style-type: none"> • Have you set 'Motion Det.' menu to OFF? • Have you set 'MD Level' to too low? • Have you set 'MD Area' properly?
The color of the picture is not matched.	<ul style="list-style-type: none"> • Check that you have properly set the 'White Bal.' menu.
The image on the screen flickers.	<ul style="list-style-type: none"> • Is the camera facing to direct sunlight or fluorescent lighting? Change the camera position. • Are you using Auto Iris Lens? Check that you have properly connected the lens plug to the Auto Iris connector on the side of the camera.
L/L mode isn't able to be selected.	<ul style="list-style-type: none"> • Have you connected your camera to DC power source? Connect it to AC power source.



Specifications

Item	SHC-721AN	SHC-721AP	SHC-721APH
Power Source	DC 12V / AC 24V compatible		AC 230V / 50Hz
Power Consumption	330mA (DC) / 4.0W (AC)		4.2W
Image Sensor	1/3", Vertical double density interline CCD		
Total Pixels	811(H) x 508(V), 1/3" CCD	795(H) x 596(V), 1/3" CCD	
Effective Pixels	768(H) x 494(V), 1/3" CCD	752(H) x 582(V), 1/3" CCD	
Scanning System	2:1 Interlaced 525 Lines/60 Fields/30 Frames	2:1 Interlaced 625 Lines/50 Fields/25 Frames	
Synchronization	Internal / Line Lock		
Video Output	1.0V(p-p) NTSC Composite, 75Ω / BNC Connector	1.0V(p-p) PAL Composite, 75Ω / BNC Connector	
Resolution	500Lines (color) / 550Lines (B/W)		
Wide Dynamic Range	Built-in (46dB)		
Day & Night	ON / OFF / AUTO 1 / AUTO 2 (Filter Auto Change)		
Gain Control	AGC-L, AGC-H, OFF Selectable		
Electronic Shutter Speed	1/60-1/200,000sec (Auto / Manual)	1/50-1/200,000sec (Auto / Manual)	
Sense up	Built-in (selectable limit -X128)		
Iris Mode	ESC / Video Drive / DC Drive		
White Balance	W-ATW / S-ATW / AWC / Manual		
Min. Illumination	Color: 0.3lux at F1.2, B/W: 0.01lux at F1.2		
S/N (Y signal)	50dB (Weight on)		
RS-232C	Built-in		
Motion Detection	MD1 / MD2 / OFF (Built-in Alarm Output Connector)		
O.S.D	Built-in		
SSNR	Built-in (LOW / MIDDLE / HIGH / OFF)		
Privacy Function	ON / OFF (4 Programmable Zone)		
Lens Mount	C / CS Mount		
Operating Temperature	-10°C ~ +50°C (14°F ~ 122°F)		
Operating Humidity	30% ~ 90% RH		
Dimension (mm)	69(W) X 56(H) X 125(D) without mounting foot & connector		
Weight (W/O Lens & Power Cord)	460g	500g	

DECLARATION OF CONFORMITY

Application of Council Directive(s) 89 / 336 / EEC
Manufacturer's Name SAMSUNG TECHWIN CO., LTD
Manufacturer's Address SAMSUNG TECHWIN CO., LTD
42, SUNGJU-DONG CHANGWON-CITY,
KYUNGNAM, KOREA, 641-120
European Representative Name _____
European Representative Address _____
Equipment Type/Environment CCTV Camera
Model Name SHC-721AP/APH
Beginning Serial NO. S404000
Year of Manufacture 2004. 4. 1
Conformance to EN 50081-1 : 1992
EMC-Directive 89/336 EEC and 92/31/EEC
EN 50130-4 : 1996

We, the undersigned, hereby declare that the equipment specified above conforms to the above Directive(s).

Manufacturer	SAMSUNG TECHWIN CO., LTD	Legal Representative in Europe
Signature	<i>Young Taek, SON</i>	Signature
Full Name	YOUNG TAEK SON	Full Name
Position	QUALITY CONTROL MANAGER	Position
Place	CHANGWON, KOREA	Place
Date	2004. 4. 1	Date

MEMO

MEMO

MEMO