



Baseline product line

ManualCallPoint Jeweller

Wireless resettable button featuring programmable scenarios



Versions:



ManualCallPoint (Green) Jeweller



ManualCallPoint (Yellow) Jeweller



ManualCallPoint (White) Jeweller




ManualCallPoint (Blue) Jeweller



Operating principle


ManualCallPoint Jeweller enables users to run pre-programmed automation scenarios with a simple press. The button can open electric locks, cut power to devices, and activate ventilation. In Fire Alarm mode, it triggers fire alarms and security sirens. Addressability ensures accurate tracking of button activations, specifying the time and room. Notifications are promptly sent to system users and CMS. Designed for emergencies, ManualCallPoint Jeweller prioritizes reliability. The button can be reset only using a special tool (key) included in the kit.






Flexibility at the core

- Two operating modes: Scenario Trigger and Fire Alarm
- In-app configuration of programmable actions
- Visual alarm verification using MotionCam detectors or any video camera connected to Ajax NVR
- Alarm delivery to CMS




Flawless hardware

- Simplified button mechanism reduces the risk of failure
- Up to 7 years of autonomous operation with pre-installed batteries
- Transparent protective lid prevents accidental alarm activation
- Tamper alarm



Smart and complex ecosystem

- Regular polling of the device to display current statuses in apps
- Automatic self-diagnosis with state reporting to the hub
- Up to 1,700 m of wireless communication and twice as much with a range extender
- Instant maintenance notifications



Quick installation and setup

- SmartBracket panel to mount the device: no need to disassemble the enclosure
- Lock to secure the device on SmartBracket
- Special tool (key) to reset the button after alarm
- Pairing with a hub via QR code
- Remote control and configuration in the app

Superior, Fibra, and Baseline product lines are mutually compatible. This opens up numerous possibilities for building systems of any configuration.

<p>Compatibility</p> <p>Hubs Hub Plus Jeweller Hub 2 (2G) Jeweller Hub 2 (4G) Jeweller Hub 2 Plus Jeweller Hub Hybrid (2G) Hub Hybrid (4G)</p> <p>Range extenders ReX ReX 2</p>	<p>Communication with hub</p> <p>Jeweller communication technology</p> <p>Frequency bands 866.0–866.5 MHz 868.0–868.6 MHz 868.7–869.2 MHz 905.0–926.5 MHz 915.85–926.5 MHz 921.0–922.0 MHz Depends on the sales region</p> <p>Communication range up to 1,700 m In an open space</p>	<p>Power supply</p> <p>Battery 2 × CR123A Pre-installed</p> <p>Battery life up to 7 years</p>	<p>Installation</p> <p>Operating temperature range from 0°C to +50°C</p> <p>Operating humidity up to 80%</p>
<p>Enclosure</p> <p>Dimensions 102 × 104 × 39 mm</p> <p>Weight 214 g</p> <p>Colour green, yellow, white, blue Depends on the selected version</p>	<p>Complete set</p> <p>ManualCallPoint Jeweller, SmartBracket mounting panel, 2 × CR123A battery (pre-installed), Special tool (key), Transparent protective lid, Installation kit, Quick start guide</p>		