

PR 302

Single Door Access Controller with Built-in RFID/PIN

Reader

- fully autonomic or networked operation
- non violate 32 000 events register
- 4 000 card users
- 250 access groups
- built-in proximity reader
- optional Wiegand or PRT(Roger) remote reader











PR 302

PR 302-BK

Ordering information

PR302

Weight

Controller with proximity and PIN reader.

PR302-BK Controller with proximity reader only (without PIN reader).

Technical specification

Operating voltage range 10...16 VDC

Current consumption	App. 80mA
Input lines	3 inputs, NO/NC type
Output lines	2 transistor outputs 1A rating
	1 relay NO/NC contacts output 1.5 DC/AC
Tamper	Normally closed contact, 24V/50mA rated
Reading range	Up to 12 cm for ISO type cards(depends of card quality)
Ingress protection	IP30

Relative humidity 10...95%

Operating temperature 0...+55°C.

Dimensions 105 X 105 X 31 mm

175 q

PR 302

ϵ

Single Door Access Controller with Build-in RFID/PIN Reader

Note: This description refer to firmware version 124.0 or higher.

Features:

- fully autonomic or networked operation
- non violate 32.000 events register
- built-in proximity UNIQUE (EM4001/2) cards reader
- · Card, PIN or [Card+PIN] identification
- 4 000 card users
- 250 access groups
- 99 time schedules, 128 periods per schedule
- · holiday settings

reader

- soft or hard local anti-passback
- optional Wiegand or PRT(Roger) remote
- biometric reader support (High Security option)

- support both side door control
- support for door contact, exit button and alarm signalization
- support XM-2 Remote I/O module
- support XM-8 Lift control module
- T&A registration
- toggle output for integration with Intruder Alarm System
- RS485 communication interface
- programming only from PC
- firmware upgrade through RS485
- Windows 95/98/NT/2K/Me/XP software
- CE Mark





roger

tel. +48 55 2720132 fax +48 55 2720133 e-mail: roger@roger.pl

www.roger.pl

All content, specifications and availability subject to change without prior notice.