

32CH Real-Time

SA-32800



■ Front Panel



■ Rear Panel



SPECIFICATIONS

| MODEL | | SA-32800 |
|--------------------|-----------------------|---|
| System | Compression Format | H.264 |
| | OS | Embedded Linux |
| Video | Input | 32CH, BNC (1.0Vp-p, 75Ω) |
| | Standard Output | 1*BNC Mainout 1*Spot 1*VGA: 1280x1024, 800x600, 1024x768, HDMI(1920*1080) |
| Audio | Audio Input | 16CH |
| | Audio Output | 1CH |
| | Two way audio | YES |
| Recording | D1(4CIF) | "330(NTSC)/275(PAL)fps,4CH D1, 28CIF real time" |
| | CIF | 960(NTSC)/800(PAL)fps |
| | Recording Mode | Schedule, Manual, Motion, Sensor |
| Playback | Playback Channel | 16CH |
| | Search Mode | Time, Event, File Management, Image(snapshot) |
| Backup | USB Disk | 1 USB2.0 port |
| | DVD Burner | Optional |
| | Backup Format | DAT or AVI |
| Remote Application | Dual Stream | Master stream: 1~25/30fps@4CIF/CIF Network stream: 1~6/7fps@CIF |
| | Browser | IE (windows XP/2000/vista/7) , Safari(Mac OS) |
| | CMS | YES |
| | 3G | SuperCam/pro/HD for iPad/iPad2/iPhone/Blackberry/Android/Symbian/Windows mobile |
| | User Access | 10 users online with professional authority management |
| Alarm | Alarm Input | 16CH |
| | Alarm Output | 4CH |
| Storage | HDD | 8SATA+2e-SATA |
| | PTZ | 2*RS485 |
| Network | Ethernet Protocol | 1,000 Mbps Ethernet (RJ-45) TCP/IP, DHCP, DDNS, NTP, SMTP |
| | Others | IR Controller |
| | Power Supply | 100VAC ~ 240VAC |
| | Operating Temperature | 0°C ~ 50°C |
| | Humidity | 10% ~ 90% humidity |