


E9. 2000 CYCLES ALERT SETTING


This function is normally OFF from factory settings.

To set a warning sound when the garage door opener reaches 2000 cycles, please carry out the following procedure:


GB




Press “-” key till the display shows “9”




Press “P” key, the display shows “0” to mean that the 2000 cycles alert is OFF



Press “+” key till the display shows “1” to set the 2000 cycles alert ON



Press “-” key till the display shows “0” to set the 2000 cycles alert OFF




Press “P” key to save the settings




Exit way to alert sound down: cut off the power supply and then turn it on again

E10. RADIO TRANSMITTERS SELECTING


Please follow the procedure to select the radio transmitter you are using:




Press “-” key to select “A”




Press “P” key, the display shows “2” (that means that dip-switches transmitter is selected)



Press “+” key, till the display shows “1” to select random code generating transmitter




Press “-” till the display shows “2” to re-select the dip-switches transmitters




Press “P” key to save settings


E11. COMMISSIONING FINALIZING



Press “+” to select “1”



Keep pressing “P” for 8 seconds



The display “0” and control unit exit the commissioning mode.



N.B. You must carry out this finalizing procedure, otherwise all the previous settings will be lost.