# Yuasa Technical Data Sheet

### Yuasa NP7-12 Industrial VRLA Battery

| <b>Specifications</b><br>Nominal voltage (V)<br>10-hr rate Capacity to 1.8V/Cell at 20°C (Ah)<br>20-hr rate Capacity to 1.75V/Cell at 20°C (Ah)                           | 12<br>6.4<br>7                                     |
|---|--|
| <b>Dimensions</b><br>Length (mm)<br>Width (mm)<br>Height over terminals (mm)<br>Mass (kg)   | 151 (±1)<br>65 (±1)<br>97.5 (±2)<br>2.2            |
| <b>Terminal Type</b><br>FASTON - Quickfit / release (JST where stated)  | 4.75   |
| <b>Operating Temperature Range</b><br>Storage (in fully charged condition)<br>Charge<br>Discharge   | -20°C to +60°C<br>-15°C to +50°C<br>-20°C to +60°C |
| <b>Storage</b><br>Capacity loss per month at 20°C (% approx.)   | 3  |
| <b>Case Material</b><br>Standard<br>FR version available  | ABS (UL94:HB)<br>UL94:V0                           |
| <b>Charge Voltage</b><br>Float charge voltage at 20°C (V)/Block<br>Float charge voltage at 20°C (V)/Cell<br>Float Chg voltage tmp correction factor from std<br>20°C (mV) | 13.65 (±1%)<br>2.275 (±1%)<br>-3                   |
| Cyclic (or Boost) charge Voltage at 20°C (V)/Block<br>Cyclic (or Boost) charge Voltage at 20°C (V)/Cell<br>Cyclic Chg voltage tmp correction factor from std<br>20°C (mV) | 14.5 (±3%)<br>2.42 (±3%)<br>-4                     |
| <b>Charge Current</b><br>Float charge current limit (A)<br>Cyclic (or Boost) charge current limit (A)   | No limit<br>1.75                                   |

# Maximum Discharge Current

| 1 second (A)                                | 210       |
|---|-----------|
| 1 minute (A)                                | 48        |
| <b>Impedance</b><br>Measured at 1 kHz (mΩ)  | 23        |
| Design Life & Approvals                     |           |
| EUROBAT Classification: Standard Commercial | 3 to 5 ye |
| Yuasa design life at 20°C (yrs)             | up to 5   |





## Layout

| $\oplus$ |  |
|----------|--|
| Θ        |  |

# 3rd Party Certifications

ISO9001 - Quality Management Systems



# Safety

#### Installation

Can be installed and operated in any orientation except permanently inverted.

## Handles

years

Batteries must not be suspended by their handles (where fitted).

### Vent valves

Each cell is fitted with a low pressure release valve to allow gasses to escape and then reseal.

### Gas release

VRLA batteries release hydrogen gas which can form explosive mixtures in the air. Do not place inside a sealed container.

#### Recycling

YUASA's VRLA batteries must be recycled at the end of life in accordance with local and national laws and regulations.



Data Sheet generated on 08/05/2024 – E&OE



www.yuasaeurope.com

