



## CCTV Varifocal Lens SLA-2985D User's Manual

Thank you for purchasing a Samsung CCTV lens.  
Before attempting to connect or operate this product,  
please read these instructions carefully and save this manual for future use.

## SAMSUNG AUTO IRIS LENS FOR CCD CAMERA OPERATING INSTRUCTIONS

SAMSUNG Lens is aimed at sharp, crisp images and exposure accuracy under even the most adverse lighting conditions.

The iris auto-close function protects imagers and optical filters from extreme high lights when power is off.

To receive the best possible results, read the instruction manual carefully before using the lens.



Samsung Techwin cares for the environment at all product manufacturing stages to preserve the environment, and is taking a number of steps to provide customers with more environment-friendly products. The Eco mark represents Samsung Techwin's will to create environment-friendly products, and indicates that the product satisfies the EU RoHS Directive.

## CONTENTS

LENS 3

PART NAMES AND FUNCTION 3

IRIS 3

HOW TO ASSEMBLE LENS AND CS MOUNT CAMERA 4

LINE BOUNDS 4


SPECIFICATIONS 5

\* Specifications are subject to change without prior notice.

## 1. LENS

This lens embeds ND filter and akes auto iris function by Galvanometer.  
And apply this lens to CCD camera that use CS mount which equip 1/3" CCD element and embed DC iris drive circuit.  
It has self focus and mount control function, operates DC iris function through lens and attached cable.

## 2. PART NAMES AND FUNCTION



## 3. IRIS

This lens have a built-in ND filter and iris by Galvanometer This iris tool is driven by inner circuit of camera.  
If power is off, its state is locked.


## 4. HOW TO ASSEMBLE LENS AND CS MOUNT CAMERA

- 1) Set Lens selection switch (DC/video) to DC location (picture 1)  
(When the lens locks successfully, it can turn around SLIP state)
- 2) Turn the lens clockwise to lock onto camera part mount screw.
- 3) Turn clockwise until stop by stopper even if it almost SLIP state.
- 4) From that point, if turn it anticlockwise, it moves 340 degree in SLIP state.  
Then set the direction as want within that range.
- 5) Turn focus lever to adjust
- 6) Finally connect of lens cable to connector of camera. (picture 2)

picture 1



picture 2




## Caution

This lens takes CS mount type so should be used 12.5mm FLANGE-BACK setting camera.

## 5. LINE BOUNDS

- ① Blue : Damping (-)
- ② Red : Damping (+)
- ③ White : Drive (+)
- ④ Green : Drive (-)



## SPECIFICATION

Model Name	SLA-2985D	
Focal Length	2.9~8.5mm	
Max. Aperture Ratio	1:1.2~300	
Max. Image Format	4.8(H) X 3.6(V)	
Operation	Iris	Auto (F1.2~300)
	Focus	Manual
	Zoom	Manual
	Diagonal	123.4" ~ 41.8"
Angle Of View	Horizontal	96.2" ~ 33.4"
	Vertical	70.7" ~ 25.1"
	Iris Type	DC
Effective Lens Aperture	Front	Ø 21.14
	Rear	Ø 8.44
Back Focal Length	7.95 to 15.3mm	
Flange Back Length	12.5mm	
Mount	CS	
Dimension(W X H X D)	38.3 X 44.7 X 45.0mm	
Weight	50g (w/o CAP)	

## SALES NETWORK

## SAMSUNG TECHWIN CO., LTD.

145-3, Sangdaewon 1-dong, Jungwon-gu, Seongnam-si, Gyeonggi-do 462-703, Korea  
TEL : +82-31-740-8137~8139 FAX : +82-31-740-8145

## SAMSUNG OPTO-ELECTRONICS UK, LTD.

Samsung House, 1000 Hillswood Drive, Hillswood Business Park Chertsey, Surrey KT16 0PS  
TEL : +44-1932-45-5308 FAX : +44-1932-45-5325

## TIANJIN SAMSUNG OPTO-ELECTRONICS CO., LTD.

7 Pingchang Rd, Nankai Dist. Tianjin 300190, P.R China  
TEL : +86-22-2761-4724(33821) FAX : +86-22-2761-6514

www.samsungtechwin.com  
www.samsungcctv.com

## DECLARATION OF CONFORMITY

Application of Council Directive(s)	89 / 336 / EEC
Manufacturer's Name	SAMSUNG TECHWIN CO., LTD
Manufacturer's Address	SAMSUNG TECHWIN CO., LTD 42, SUNGJU-DONG CHANGWON-CITY, KYUNGNAM, KOREA, 641-716
European Representative Name	
European Representative Address	
Equipment Type/Environment	CCTV CAMERA LENS
Model Name	SLA-2985D
Beginning Serial NO.	J202001
Year of Manufacture	2006. 6. 1
Conformance to	EN 55022 : 1988 Class A EN 501304 : 1995 / AI : 1988

We, the undersigned, hereby declare that the equipment specified above conforms to the above Directive(s).

Manufacturer	SAMSUNG TECHWIN CO., LTD	Legal Representative in Europe
Signature	Young Taek, SON	Signature
Full Name	YOUNG TAEK SON	Full Name
Position	QUALITY CONTROL MANAGER	Position
Place	CHANGWON, KOREA	Place
Date	2006. 6. 1	Date