

# CA-10


# Satel®

Thanks to its multitude of features the CA-10 system provides optimum protection for medium and small-size objects.



### *System features*

- up to 16 zones
  - 8 on-board zones
  - 2 zones on each keypad
  - expandable by adding keypads or zone expansion modules
  - 20 zone functions
  - detector trouble monitoring feature
- 6 outputs
  - 4 high power outputs 2,2A
  - 2 open collector outputs
  - fully programmable
  - 40 functions
- 4 partitions
- system controlling
  - LCD and LED keypads
  - DTMF telephone using optional MST-1 module
- programming
  - local by LCD and LED keypad
  - local by PC via RS-232
  - remote by integrated 300bps modem or external modem
- event log
  - non-volatile
  - 255 entries
  - arm, disarm, trouble, alarm
  - user functions
  - event timestamp
- codes
  - 1 service code
  - 1 master code
  - up to 13 user codes per partition
  - up to 32 user codes total
- 4 timers
  - automatic arm, disarm etc.
  - supervision of guards
- telephone dialer
  - monitoring – 2 monitoring station numbers
  - call answering for remote system supervision
  - voice and text messaging
  - remote programming with PC via modem
- telephone signal analysis
  - TBR-21 compatible telephone signal recognition
  - advanced algorithm for re-transmission attempts
- messaging
  - 8 telephone numbers (SM-2 voice synthesizer)
  - 1 voice message
  - 4 text messages sent as SMS or to pagers
- RS-232
  - local programming
  - serial printer connection
- switching mode power supply
  - 2,2A total capacity
  - short-circuit protection
  - battery condition testing
  - deep discharge battery protection
- on-line event printout
  - corresponds to monitoring station printout
  - optional event filtering
  - input, module and user names printed according to system definition
- on-line diagnostics of key system components
- CE Declaration of Conformity



### *CA-10 E Zone module*

- 6 zones
- connected instead of one keypad



### **CA-10 KLCD Keypad**

- LCD display
  - 2x16-character display
  - text messages
  - event log readout
  - system clock and date
  - partition status display
  - system status display
- keypad and LCD display backlight - permanent or temporary
- hold-down FIRE, PANIC and AUX alarm
- sound signals
  - alarm
  - trouble
  - entry delay
  - exit delay
  - chime on door entry
  - keypad action confirmation
- 2 zones
  - NO, NC, EOL, 2EOL/NO or 2EOL/NC configurations
  - 20 functions
  - detector trouble monitoring feature
- 6 LEDs
  - partition status display - ARMED, ALARM
  - system status display - TROUBLE
- tamper switch
- programming via RS-232
- definition of user, partition and zone names for easier controlling, supervising and event log analysis


### **CA-10 KLCD-L and CA-10 KLCD-S Keypads**

- LCD display
  - 2x16-character display
  - text messages
  - event log readout
  - system clock and date
  - partition status display
  - system status display
- keypad and LCD display backlight – permanent or temporary
- hold-down FIRE, PANIC and AUX alarm
- 6 LEDs
  - partition status display - ARMED, ALARM
  - system status display - TROUBLE
- sound signals
  - alarm
  - trouble
  - entry delay
  - exit delay
  - chime on door entry
  - keypad action confirmation
- 2 zones
  - NO, NC, EOL, 2EOL/NO or 2EOL/NC configurations
  - 20 functions
  - detector trouble monitoring feature
- tamper switch
- programming via RS-232
- definition of user, partition and zone names for easier controlling, supervising and event log analysis



### **MST-1 DTMF Module**

- system control by DTMF telephone
- system and zone status supervision
- CA-10 plus (4.2 and later) compatible



### **SM-2 Voice synthesiser**

- voice message with alarm information
  - message time - up to 16 seconds
  - stored in non-volatile memory
- built-in microphone
- 2 earphone jacks for telephone line and recording supervision



### CA-10 KLED-S Keypad

- 23 LEDs
  - status of 16 zones
  - partition status display - ARMED, ALARM, exit delay
  - system status display - TROUBLE
- keypad backlight - permanent or temporary
- hold-down FIRE, PANIC and AUX alarm
- sound signals
  - alarm
  - trouble
  - entry delay
  - exit delay
  - chime on door entry
  - keypad action confirmation
- 2 zones
  - NO, NC, EOL, 2EOL/NO or 2EOL/NC configurations
  - 20 functions
  - detector trouble monitoring feature
- tamper switch
- keypad bus failure indication



### CA-10 KLED Keypad

- 15 LEDs
  - status of 12 zones
  - partition status display - ARMED, ALARM, exit delay
  - system status display - TROUBLE
- keypad backlight
- hold-down FIRE, PANIC and AUX alarm
- sound signals
  - alarm
  - trouble
  - entry delay
  - exit delay
  - chime on door entry
  - keypad action confirmation
- 2 zones
  - NO, NC, EOL, 2EOL/NO or 2EOL/NC configurations
  - 20 functions
  - detector trouble monitoring feature
- tamper switch



### DLOAD 10

#### Alarm system installer software

- Windows 98/ME/2000/XP compatible
- complete system programming features
- full on-line system diagnostics
- system event log readout
- user-friendly interface
- virtual keypad
- control panel connection
  - direct via RS-232 on main board



CA-10

**Satel®**  
www.satel.pl